



(Rear of connector VIEW)

No.	26 Pin Standard	Polecam Interface
A	POWER (+) IN	No connection
B	POWER (-) IN	
1	Video OUT	VBS 1.0 Vp-p, Zo=75 Ω
2	Video ground	
3	Ground (Y)	
4	Y Output	VS 1.0 Vp-p, Zo=75
5	R-Y Output	Zo=75
6	Ground (R-Y)	
7	B-Y Output	Zo=75
8	Ground (B-Y)	
9	Audio Output (hot)	Zo ≤ 1000 Ω,
10	Audio Output (cold)	-10 dBu balanced
11	Audio Screen	
12	VTR START/STOP OUT	START: 5±1 Vdc, STOP: 0 ±0.2 Vdc, Zo ≤ 10 kΩ
13	BATT IND IN	No connection
14	NC	No connection
15	REC ALARM IN	Zi ≥ 20 kΩ
16	NC	No connection
17	GND (SHIELD)	Camera GND
18	Video Input (ret. video)	VS 1 Vp-p, Zi=75 Ω
19	Video Ground	
20	AUDIO MONITOR IN/ VTR SAVE OUT	No connection
21	NC	No connection
22	CF OUT	No connection
23	NC	No connection
24	NC	No connection